



WIRING RULES

1. MARK 'START' AT END OF CABLE.
2. ALWAYS START OFF IN A CLOCKWISE DIRECTION ON ENTRY FROM KERB.
3. ALWAYS CHANGE DIRECTION AT THE CENTRE (LONGITUDINAL) CUT TO MAKE A 'FIGURE 8' PATTERN.
4. ALWAYS FORM THREE 'FIGURE 8' PATTERNS FOR EACH LOOP SECTION.
5. THERE ARE TWO IDENTICAL QUADRUPOLE LOOPS REQUIRED FOR EACH BICYCLE LANE APPROACH WHICH ARE INSTALLED IN ADJACENT LOGITUDINAL SAWCUTS REFER TO VC005-36.

	REFERENCE DRAWINGS	
	METHOD OF INSTALL	VC005-36

ROADS AND MARITIME SERVICES TRAFFIC SIGNALS	SCALE	APPROVED
		SUNIL SRIVASTAVA 06-06-2012
QUADRUPOLE TYPE BICYCLE LOOP DETECTOR WIRING GUIDE FOR 4 POSSIBLE ENTRY POSITIONS	SUPERSEDES:	ISSUE
	DRAWN D. BAIGORRIA	A
	CHECKED L. CLAY	
	PASSED B.W. TAYLOR	VC005-37